



Atlas Audio

Ceiling Coax Speaker Motor Board

FA62T-8MB

SKU: 25073 UPC: 612079179817

Model FA62T-8MB is the entire 6" Loudspeaker/ transformer/ selector switch/ front plate assembly found in the FAP62T assembly. The footprint of the FA62T-8MB is identical to a standard FA series 8" Loudspeaker component. This footprint allows the motor board to fit into all original Strategy Series 8" enclosures in the exact same manner as a regular 8" FA Loudspeaker(FA138Txx).

Features:

- 6" Speaker Installs into 8" Strategy Enclosure
- Designed for Division of Labor Installations When Enclosures Need to be Installed Before Speakers
- Enhanced Quality 70.7V/100V Internal Transformers Minimize Insertion Loss and Maintain Low Frequency Response While Providing increased Output for Higher SPL Applications
- Front Mounted Tap Selector Switch for Easy System Tuning Adjustments Includes Transformer Bypass Setting for 8 ohm Direct Coupled Operation
- Tuned Port Maximizes Low Frequency Response from FA97-8 & FA95-8 Enclosure
- UL1480 for General Signaling Listed file UEAY.S1824

Speaker Type	Coaxial
Sensitivity	88dB Average
Frequency Response	63Hz - 20kHz
Impedance	2, 4, 8, 16, 32, 8 Ohm direct
Dispersion	110°
Depth	5 1/2" (13.97 cm)
Diameter	8 1/2" (21.59 cm)
Shipping Weight	6.00 lbs (2.72 kgs)
Safety Listed	1480